WATELH

HTH7G14S030H(B) 30W, 1.8 - 1400 MHz LDMOS Amplifier

Product datasheet

Description

The HTH7G14S030H(B) is an unmatched discrete LDMOS Power Amplifier with 30W saturated output power covering frequency range from 1.8 - 1400 MHz.

Features

Operating Frequency Range: 1.8 - 1400 MHz

Operating Drain Voltage: 28-50V

Saturation Output Power: 30W

 Excellent thermal stability due to low thermal resistance package

Enhanced robustness design without device degradation


Internally integrated enhanced ESD design

Applications

- Analog and Digital Broadcasting
- Meteorological and Aviation Radar
- Private network communication base station
- Industrial Laser Sources and Plasma Equipment
- Various nuclear magnetic resonance instruments
- Particle accelerator

Ordering Information

Part Number	Description	
HTH7G14S030H(B)	Tray Package	
HTH7G14S030H(B) EVB	1400MHz EVB	



HTH7G14S030H(B) 30W, 1.8 - 1400 MHz LDMOS Amplifier



Product datasheet

RF Characteristics (CW)

Freq (MHz)	P1dB (dBm)	Eff (%)@P1dB	Gain (dB)	P3dB (dBm)	Eff(%)@P3dB
2	42.91	76.15	30.74	44.38	85.21
5	43.13	77.49	30.61	44.38	85.59
15	43.37	77.00	29.92	44.37	83.93
30	43.51	74.85	28.69	44.50	81.47

Test conditions unless otherwise noted: 25 °C, VDD = +48Vdc, IDQ = 160mA ,Vgs=2.97V CW test on WATECH Application Board

RF Characteristics (Pulsed CW)

Freq (MHz)	P1dB (dBm)	Eff (%)@P1dB	Gain (dB)	P3dB (dBm)	Eff(%)@P3dB
1400	44.89	59.55	17.16	45.64	62.04

Test conditions unless otherwise noted: 25 °C, VDD = +50Vdc, $IDQ = 100mA\ PW = 100us$, DC = 10% test on WATECH Application Board

Absolute Maximum Ratings

Parameter	Range/Value	Unit
Drain voltage (VDSS)	-0.5 to +105	V
Gate voltage (V _{GS})	-6 to +10	V
Storage Temperature (Tstg)	-55 to +150	°C
Junction Temperature (T _J)	+225	°C

Electrical Specification

DC Characteristics

Parameter	Conditions	Min	Тур	Max	Unit
Breakdown Voltage V(BR)DSS	Vgs=0V, Ids=100uA	105	-	-	V
Gate-Source Threshold	Vgs=Vds, Ids=100uA	1.8	2.1	2.4	V
Voltage V _{GS(th)}	V63-V43, 143-1004/	1.0	2.1	۷.٦	V
Drain Leakage Current loss	Vgs=0V, Vds=50V	0.5	5	100	nA
Gate Leakage Current Igss	Vgs=5V, Vds=0V	0.5	3	100	nA

Load Mismatch Test

Condition	Test Result
VSWR=65:1, at all Phase Angles, V _{DD} = +50Vdc, I _{DQ_Carrier} = 100mA,	No Device
CW PAVG = 30W, Frequency 1400MHz test on WATECH Application Board	Degradation



HTH7G14S030H(B)

Product datasheet





Thermal Information

Parameter	Condition	Value (Typ)	Unit
Thermal Resistance	V _{DD} =50V,I _{DQ} =150mA,T _{case} =25°C,PL=30W,C	2 -	°C /W
Junction to Case (Rтн)	W	3.5	C / VV

Load Pull Performance Carrier


Test conditions unless otherwise noted: 25 °C, VDD = +50Vdc, IDQ= 100mA, PW = 40us, DC= 4%

	Max Output Power						
Freq	Z _source	Z_load [1]	Gain	P3dB	P3dB	Eff	
(MHz)	(Ω)	(Ω)	(dB)	(dBm)	(W)	(%)	
1200	1.85+2.5	7.72+6.62	19.50	46.62	45.92	64.8	
1400	1.76+0.88	5.4+4.75	18.30	46.67	46.45	63.3	

[1] Load impedance for optimum P3dB pout

	Max Drain Efficiency						
Freq	Z _source	Z_load [2]	Gain	P3dB	P3dB	Eff	
(MHz)	(Ω)	(Ω)	(dB)	(dBm)	(W)	(%)	
1200	1.85+2.5	5.9+8.65	20.52	46.15	41.21	71.03	
1400	1.76+0.88	4.73+7.67	20.40	45.90	38.90	70.92	

[2] Load impedance for optimum P3dB efficiency



Z_source : Measured impedance presented to the input of the device at the package reference plane

Z_load: Measured impedance presented to the output of the device at the package reference plane




HTH7G14S030H(B)

Product datasheet

30W, 1.8 - 1400 MHz LDMOS Amplifier

HTH7G14S030H(B)

1400MHz Reference Design



EVB Layout

Bill of Materials (BoM) - HTH7G14S030H(B)

1400MHz Reference Design

Reference	Value	Description	Manufacturer	P/N
Q1	_	30W, 1.8 - 1400 MHz	Watech	HTH7G14S030H(B)
Q1		LDMOS PA	vvateen	111117 014303011(b)
C1	16pF	0805 Chip Capacitor	Murata	GQM2195C2E160GB12D
C2\C5\C7\C11	47pF	0805 Chip Capacitor	Murata	GQM2195G2E470JB12D
C3	5.6pF	0805 Chip Capacitor	Murata	GQM2195C2E5R6BB12D
C4	2.7pF	0805 Chip Capacitor	Murata	GQM2195C2E2R7CB12D
C9	1.5pF	0805 Chip Capacitor	Murata	GQM2195C2E1R5BB12D
C10	6.8pF	0805 Chip Capacitor	Murata	GQM2195C2E6R8CB12D
C6/C8	10uF	1210 Chip Capacitor	Murata	GRM32ER61H106KA12L
R1	7.5 Ω	0805 Chip Resistor		
R2	1.6k Ω	0805 Chip Resistor		
РСВ	Rogers 43	50B (er = 3.5), 20 mil, 35	5 μm (1oz)	

30W, 1.8 - 1400 MHz LDMOS Amplifier

Product datasheet



CW, Gain and Efficiency vs Pout

Test conditions unless otherwise noted: 25 °C, VDD = +48Vdc, IDQ = 160mA, Vgs=2.97V test on WATECH Application Board



Pulsed CW, Gain and Efficiency vs Pout


Test conditions unless otherwise noted: 25 °C, VDD = +50Vdc, IDQ= 100mA , PW = 100us, DC= 10% test on WATECH Application Board



30W, 1.8 - 1400 MHz LDMOS Amplifier

Product datasheet


Package Marking and Dimensions




- Line1 (fixed): Device name in W/O
- Line2 (unfixed): HT+Date Code

This Marking SPEC only stipulates the content of Marking. For marking requirements such as font and size, please refer to the latest version of "Watech Product Printing Specification"

Marking





Symbol	Dimens	ions In Mil	limeters	Dimensions In Inches		
3,111001	Min.	Mon.	Max.	Min.	Mon.	Max.
Α	3.84	3.98	4.12	0.151	0.157	0.162
В	5.37	5.50	5.63	5.211	0.217	0.222
С	0.11	0.13	0.15	0.004	0.005	0.006
D	9.07	9.20	9.33	0.357	0.362	0.367
D1	9.07	9.20	9.33	0.357	0.362	0.367
E	5.67	5.80	5.93	0.223	0.228	0.233
E1	5.67	5.80	5.93	0.223	0.228	0.233
F	1.37	1.50	1.63	0.054	0.059	0.064
Н	17.30	17.80	18.30	0.681	0.701	0.720
Q	1.95	2.08	2.21	0.077	0.082	0.087
U2	5.67	5.80	5.93	0.223	0.228	0.233

Package Dimensions


HTH7G14S030H(B)



30W, 1.8 - 1400 MHz LDMOS Amplifier

Product datasheet

ACC0906S-4L Earless Flanged Air Cavity Ceramic Package; 2 Leads



	Dimesions in Milimeters			Dimesions in Inches		
Symbol	Min.	Mon.	Max.	Min.	Mon.	Max.
A	3.84	3.98	4,12	0.151	0.157	0.162
b	5.37	5.50	5.63	5.211	0.217	0.222
c	0.11	0.13	0.15	0.004	0.005	0.006
D	9.07	9.20	9.33	0.357	0.362	0.367
E	5.67	5.80	5.93	0.223	0.228	0.233
F	1.37	1.50	1.63	0.054	0.059	0.064
G	1.07	1.20	1.33	0.042	0.047	0.052
Н	17.30	17.80	18.30	0.681	0.701	0.720
p	3.05	3.3	3.55	0.120	0.130	0.140
q	14.07	14.20	14.33	0.554	0.559	0.564
U1	20.17	20.30	20.43	0.794	0.799	0.804

Package Dimensions

ACC0906B-2L Flanged balanced Air Cavity Ceramic Package; 2 Leads; 2 Mounting Holes

30W, 1.8 - 1400 MHz LDMOS Amplifier

Product datasheet

Tape and Reel Information

Package Type	Qty/Tray(pcs)	Qty/Box(pcs)
ACC0906B-2L	30	300



Tape & Reel Packaging Descriptions

Handling Precautions

Parameter	Grade
Moisture Sensitivity Level MSL	3

Parameter	Rating	Standard	
ESD – Human Body Model (HBM)	Class 1B	JESD22-A114	
ESD – Human Body Model (MM)	Class A	EIA/JESD22-A115	
ESD – Charged Device Model (CDM)	Class III	JESD22-C101	



RoHS Compliance

This product is compliant with the 2011/65/EU RoHS directive (Restrictions on the Use of Certain Hazardous Substances in Electrical and Electronic Equipment), as amended by Directive 2015/863/EU.

Datasheet Status

Document status	Product status	Definition
Objective Datasheet	Design simulation	Product objective specification
Preliminary Datasheet	Customer sample	Engineering samples and first test results
Product Datasheet	Mass production	Final product specification



HTH7G14S030H(B) 30W, 1.8 - 1400 MHz LDMOS Amplifier

Product datasheet

Abbreviations

Acronym	Definition
LDMOS	Laterally-Diffused Metal-Oxide Semiconductor
CW	Continuous Waveform

Revision history

Document ID	Datasheet Status	Release Date	Revision Version
Rev 1.4	Objective	March 2023	New format based on English version datasheet
Rev 2.0	Product	Sept. 2023	Update TBD information
Rev 2.1	Product	March 2024	Version released after re review

HTH7G14S030H(B) 30W, 1.8 - 1400 MHz LDMOS Amplifier



Product datasheet

For the latest specifications, additional product information, worldwide sales and distribution locations and information about WATECH:

• Web: <u>www.watechelectronics.com</u>

• Email: MKT@huatai-elec.com

For technical questions and application information:

Email: MKT@huatai-elec.com

Important Notice

Information in this document is believed to be accurate and reliable. However, WATECH does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

"Typical" parameters are the average values expected by WATECH in large quantities and are provided for information purposes only. All information and specifications contained herein are subject to change without notice and customers should obtain and verify the latest relevant information before placing orders for WATECH products.

The information contained herein or any use of such information does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other intellectual property rights, whether with regard to such information itself or anything described by such information.

Applications that are described herein for any of these products are for illustrative purposes only. WATECH makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification. Customers are responsible for the design and operation of their applications and products using WATECH products, and WATECH accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the WATECH product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third-party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

WATECH products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety- critical systems or equipment, nor in applications where failure or malfunction of a WATECH product can reasonably be expected to result in personal injury, death or severe property or environmental damage. This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.